LiteShow3 Manual

Step 1: Welcome Screen

• Welcome Screen of LiteShow3 Adapter on Projector

LOGIN CODE: 1111 LOGIN CODE: 1111				
To begin projecting over the LAN, the LITESHOW application must be installed and running on your computer. This application is needed to manage the communication between your computer and the LITESHOW module				
INSTRUCTIONS				
 1) Download and install the LITESHOW application, if not already installed on your computer a) Connect the LITESHOW module to a display (and to a network, if desired). b) Turn on the LITESHOW module and display. The LITESHOW splash screen should appear within one minutes of your must be connected to the LITESHOW module through a wired or wireless LAN. For wireless LAN, connect to the wireless network using the same SSID as shown on the display. d) Enter the IP address displayed on the display into your web browser. e) Login as NONE and select SOFTWARE DOWNLOAD. f) Download the LITESHOW application 				
2) Run the LITESHOW application a) At the Access Point prompt, select t SKIP for a wired LAN connection. b) Select the LITESHOW module from t c) Enter the Login Code, if enabled.	he appropriate wireless connection to the LITESHOW module or chothe Device List.			
3) Begin presenting				
l				
Server IP: 172.16.132.125	SSID: Wifi Projector 22-132			
Resolution: 800x600	Channel: 6			
Version: 1.0.1.6	Security: None			

Step 2: Connect to Wifi

• Connect Wi-Fi of the Laptop according to Room number .i.e. Wi-Fi Projector 22-132



Step 3: Download, Install and Run LiteShow3 application

- Liteshow3 client software needs to be installed and it can be found at ccse-software or on infocus website as follows:
 - o <u>\\ccse-software.pc.ccse.kfupm.edu.sa\Applications\Drivers\Projector\Liteshow</u>
 - o <u>http://www.infocus.com/peripherals/INLITESHOW3#downloads</u>
- Once connected to Wi-Fi, run Liteshow3 software.

S Skype	40	
TeamViewer 11	hpmini Documents	
Getting Started	Pictures Music	
WordPad	Games Computer	
Microsoft Office Excel 2007	Control Panel Devices and Printers	
Get Unline All Programs	Default Programs Help and Support	
Search programs and files	Shut down	EN

<u>Step 4</u>

• Connecting to Liteshow3.



Step 5: Connect to Access Point

• Connect to the access point by selecting the "SSID" corresponding to the Room number.



Step 6: Select the Device

• It will show the Device name along with IP Address. Select the device with the IP address/device name with that on the welcome screen.

	Device Name	×
	Available Server List IP Address Device Name 172.16.132.125 Wifi Projector 22-132 172.16.132.122 WiFi Projector 22-130 172.16.0.180 LiteShow3	
	OK Skip	
*		
		EN 🔺 醋 🛈 🚯 л 🍽 3119 PM

Step 7: Insert login code

• Put login code. Default is "1111". Also available on login screen.



<u>Step 8</u>

• Login code inserted.

Step 9: Screen Resolution

• For some laptops it will ask to adjust resolution of screen. Press OK.

• Screen after successful connection.